

### Cleaning:

- > Clean this light fitting only with a soft dry cloth, do not use any chemical or abrasive cleaners.

### Tube replacement:

- > Switch off the electricity at the mains.
- > Remove the diffuser ( diffuser model ) or tube retaining brackets ( non-diffused model ).
- > Rotate the tube through 90° at both ends and pull it out of the gap.
- > Fit only Eterna® branded tubes of the same type and size.
- > Re-fit the diffuser or tube retaining brackets.

### Replacement tube type:

- > The light source in your striplight is a bespoke array of LEDs. These LEDs have a life expectancy of many tens of thousands of hours and so are unlikely to need replacing within the lifetime of the fitting.
- > If one or more of the LEDs do not light, you will need to replace your light fitting, there are no user serviceable parts inside.

### Eventually, you may want to replace this light fitting:

When your light fitting comes to the end of its life or you choose to update or upgrade it by replacing it, please do not dispose of it with your normal household waste, please recycle where facilities exist. When you need to dispose of this fitting, check with your retailer or local authority for suitable options. New regulations require the recycling of Waste from Electrical and Electronic Equipment ( European "WEEE Directive" effective August 2005—UK WEEE Regulations effective 2nd January 2007 ).  
Environment Agency Registered Producer: WEE/GA0248QZ



### If you experience problems:

If your light is defective or develops a fault, please return it to the place where you bought it. You can call our Helpline for advice. The Helpline will gladly give advice on any aspect of any Eterna Lighting product but may not be able to give specific instructions regarding individual installations.  
If in doubt, consult a qualified electrician.

### Help line:

Tel: 01933 673 144      Fax: 01933 678 083      Email: [sales@eterna-lighting.co.uk](mailto:sales@eterna-lighting.co.uk)  
For answers to frequently asked questions ( FAQs ) and other information visit our web-site  
[www.eterna-lighting.co.uk](http://www.eterna-lighting.co.uk)



# IMPORTANT!

## Safety and Installation instructions

## LED Striplight

**Model(s)**  
LEDS15WH, LEDS27WH

### Pack contents:

LED striplight	1
End socket cover	1
Link&Light® 2m mains lead	1
Fixing clips ( 2 types )	4
Fixing pack	1

**PLEASE READ THESE INSTRUCTIONS BEFORE  
INSTALLING YOUR NEW FITTING**

**PLEASE RETAIN FOR FUTURE REFERENCE**

## Read this first:

- > Check the pack and make sure you have all of the parts listed on the front of this booklet. If not, contact the outlet where you bought this product.
- > This light fitting must be installed by a competent person in accordance with the Building Regulations making reference to the current edition of the IEE Wiring Regulations (BS7671). The Building Regulations may be obtained from HMSO or viewed and downloaded from [www.communities.gov.uk](http://www.communities.gov.uk) following the link for Building Regulations.
- > As the buyer, installer and/or user of this product it is your own responsibility to ensure that this fitting is fit for the purpose for which you have intended it. Eterna Lighting cannot accept any liability for loss, damage or premature failure resulting from inappropriate use.
- > If in any doubt, consult a qualified electrician.
- > This product is designed and constructed according to the principles of the appropriate British Standard and is intended for normal domestic service. Use of this fitting in any other environment, for example where prolonged periods of use may be expected and/or higher than normal ambient temperatures, may result in a foreshortened working life.
- > Switch off the mains before commencing installation and remove the appropriate circuit fuse.
- > Suitable for indoor use only.
- > This product is suitable for installation on surfaces with normal flammability (indicated by the "F" in a triangle) e.g. wood, plasterboard, masonry. It is not suitable for use on highly flammable surfaces (e.g. polystyrene, textiles).
- > Before making fixing hole(s), check that there are no obstructions hidden beneath the mounting surface such as pipes or cables.
- > Do not attach to surfaces which are damp, freshly painted or otherwise electrically conductive (e.g. metallic surfaces).
- > If the location of your new fitting requires the provision of a new electrical supply, the supply must conform with the requirements of the Building Regulations making reference to the current edition of the IEE Wiring Regulations (BS7671).
- > This product is designed for permanent connection to fixed wiring: this should be either a suitable lighting circuit

(protected with a 5 or 6 Amp MCB or fuse) or a fused spur (with a 3 Amp fuse) via a fused connection unit. We recommend that the supply incorporates a switch for ease of operation.

- > The cores in the mains lead are coloured in accordance with the following code:  
Live - Brown or Red  
Neutral - Blue or Black
- > When making connections, ensure that the terminals are tightened securely and that no strands of wire protrude. Check that the terminals are tightened onto the bared conductors and not onto any insulation. Wrap loose terminal blocks well with insulating tape.
- > This fitting is double insulated, do not connect any part to earth.
- > **IMPORTANT**— Always switch off at the socket and remove the plug before changing the lamp.
- > A maximum of six fittings may be linked together in one chain.
- > You are advised at every stage of your installation to double-check any electrical connections you have made. After you have completed your installation there are electrical tests that should be carried out: these tests are specified in the Wiring Regulations (BS7671) referred to in the Building Regulations. If in doubt, consult a qualified electrician.

## Installation:

- 1) Select the type of brackets you need to use and mark off the fixing points. If fixing to a shelf or under a cupboard, check the screw size required and screw into place. See figures 1 and 2, opposite.
- 2) If fixing directly to the wall, drill holes using a N°8 / 5mm drill bit to a depth of 30mm and insert wall plugs.
- 3) Secure the selected brackets in place using the screws supplied.
- 4) Attach the fitting to the clips.
- 5) Connect the mains lead or link lead (not supplied) to the socket on your fitting.
- 6) Restore the power supply and switch on.
- 7) Note that when installed and connected in a chain with other Link&Light fittings, the switch in your fitting will turn the fitting on and off but have no effect on any other fittings in the chain or the power routed through.

## Warning:

The leads supplied with your light fitting and the sockets incorporated in your fitting are designed to give protection against any possible electrical hazard. The mains lead is terminated in a socket marked NLS and this lead should be used to supply mains to your fitting or chain of fittings. Under no circumstances should you attempt to adapt the link lead to supply power to the opposite end of your fitting as this will leave live pins exposed at the mains input end of the fitting. Altering or adapting any of the leads, other than shortening the mains supply lead, will invalidate your guarantee and could present a severe electrical shock hazard.

Safety markings:



## How to link multiple fittings together.

Option 1. The light fittings can be butted together to form a line of up to a maximum of 6 fittings. Simply remove the connector caps and push the fittings together. Use the mains lead cable to connect the first fitting and the mains via a spur or junction box (not supplied).

Option 2. Connect link leads (available separately) between each fitting and once all lights have been connected, connect the mains lead to the mains via a spur or junction Box (not supplied).

Option 3. For more than one unlinked light, use a socket block (available as an optional extra) and simply plug the plug into your nearest socket outlet.

